

**PIR detector via radio with anti-pets**

- U-Prox PIR detector with anti-pets
- 12 meter detection range
- Adjustable sensitivity from the U-Prox installer app
- Up to 5 years of operation with a CR123 battery
- Easy to install
- RF frequency 868 ~ 868.6MHz
- Multiple channels for redundancy
- Range of up to 4800 meters
- Compact size

**Reference / Model****UPROX-017 / U-Prox PIR WHITE****specs**

12 meter detection range  
Tolerance to pets up to 20 kg  
ISM band radio interface, multi-speed with several channels  
RF frequency: 868 ~ 868.6MHz  
Secure two-way communication with tamper detection and 256-bit key  
Optical noise immunity:> 6500 lux  
Immunity to electromagnetic fields: 5 V / m  
Resistance to electrostatic discharge: 8 kV  
Power: CR123A lithium battery (included)  
Consumption: <10  $\mu$ A (standby), <20 mA (active)  
Battery life of up to 5 years  
-10 ° C ~ + 55 ° C operating temperature  
White housing  
Dimensions: 60 (W) x 90 (H) x 34.35 mm  
Weight: 130g